

## Model 3030P Alpha/Beta Sample Counter

### Features

- Fully Integrated Alpha Beta Sample Counter
- Simultaneous Alpha and Beta Counting
- Employs PIPS™ Detector
- Ultra Low A/B Crossover & Backgrounds
- Adjustable Alpha Window for Radon Reduction
- Data Logging with USB Connectivity
- Configurable Daily QC Routines
- Holds Samples up to 5.1 cm (2 in.) Diameter & 1.02 cm (0.4 in.) Thick (with provided insert)
- Includes PC Software



### Introduction

The 3030P's solid state PIPS™ detector facilitates efficient and cost-effective, simultaneous alpha and beta sample counting for air filters, smears, and swipes. This instrument meets the newer Electric Power Research Institute (EPRI) guideline for detecting a few disintegrations per minute of alpha amidst several hundred-thousand disintegrations per minute beta background. All data are automatically logged and easily retrievable via a USB connection. The light weight and battery operability afford convenient use in the field.

With the optional detector shield, the Model 3030P can be used in virtually any background. The instrument comes with PC control software that allows the user to set all parameters, view QC check settings, change alpha and beta window and threshold values, perform MDA (Minimum Detectable Activity), and retrieve the sample data saved to the logging memory.

PIPS™ is a registered trademark of Canberra Industries, Inc.

### Specifications

Part Number: 48-3509

**DETECTOR:** solid-state silicon detector

**ACTIVE AND OPEN AREA:** 1700 mm<sup>2</sup>

**ALPHA EFFICIENCY (4π geometry):** <sup>239</sup>Pu: 35%; <sup>241</sup>Am: 30%

**BETA EFFICIENCY (4π geometry):** <sup>99</sup>Tc: 15%; <sup>137</sup>Cs: 23%; <sup>90</sup>Sr/<sup>90</sup>Y: 36%

**BACKGROUND (approx. 10 μR/hr field):** alpha - 3 counts or less in 10 minutes (≤ 0.3 cpm); beta - 350 counts or less in 10 minutes (≤ 35 cpm)

**CROSSTALK (approx. 10 μR/hr field):** alpha - 5% or less; beta - 0.1% or less

**SAMPLE SIZE:** capable of holding 2.5 cm (1 in.) or 5.1 cm (2 in.) diameter samples (with provided insert), up to 1.02 cm (0.4 in.) thick

**SCALERS:** two each (one per channel), six-digit LCD displays with backlights providing a range of 0–999,999 counts (started by COUNT button)

**SCALER LINEARITY:** reading within 2% of true value

**COUNT TIMER:** single timer, switch adjusts from 0.1–60 minutes (0.1, 0.5, 1, 2, 5, 10, 60) or selects PC (PC is a user-customizable setting that allows user-defined counts from 0.1 to 1666.6 minutes)

**ALARM:** alpha, beta, and alpha+beta alarms are user-settable

**STATUS INDICATORS:** backlit indicators for

- QC: daily Quality Control check needed
- LOW BATT: battery power is low
- CPM/DPM: counting in CPM or DPM mode
- αAL/βAL: count has exceeded alarm setpoint

**BACKGROUND SUBTRACT:** may be subtracted automatically in either CPM or DPM modes

**INTERFACE:** USB - includes a 1 meter (39 in.) USB cable for connection to a PC

**SOFTWARE:** free PC interface software allows parameter setup and data logging

**AUDIO:** built-in unimorph type speaker with volume control to provide a dual tone click-per-event audio

**POWER:** universal AC input (95-250 Vac, 50-60 Hz) wall-mount supply outputting 5 Vdc at up to 1 amp, or four "D" cell batteries

**BATTERY LIFE:** 48 hours

**TEMPERATURE RANGE:** -20 to 50 °C (-4 to 122 °F)

**CONSTRUCTION:** aluminum housing with powder coat finish, subsurface printed front panel

**SIZE:** 19 x 20.3 x 25.4 cm (7.5 x 8 x 10 in.) (H x W x D), including handle in height and drawer handle in depth

**WEIGHT:** approximately 3.9 kg (8.5 lb), or approximately 8.4 kg (18.5 lb) with the optional detector shielding

**OPTIONAL SHIELDING KIT:** reduces beta background by approximately 20% (Part No. 4337-291)

Ludlum Measurements, Inc. P.O. Box 810, Sweetwater, Texas 79556

Web: <http://www.ludlums.com> Tel: 800-622-0828 / 325-235-5494 / Fax: 325-235-4672 / Email: [sales@ludlums.com](mailto:sales@ludlums.com)

Note: specifications subject to change without notification. We are not responsible for errors or omissions.